

The IDP-Series Duplex Pump Control Panels consist of TWO IEC rated motor starters with Class 10 adjustable motor overloads, short circuit protection and a fused disconnect.

### 230 Volt

Motor Voltage 60Hz	Max HP	Overload Relay Range	NEMA 12/3R	NEMA 4	NEMA 4X 304SS
230V	2	5.5-8	IDP2002N312	IDP2002N4	IDP2002N4X
230V	3	9-13	IDP2003N312	IDP2003N4	IDP2003N4X
230V	5	12-18	IDP2005N312	IDP2005N4	IDP2005N4X
230V	7.5	16-24	IDP2007N312	IDP2007N4	IDP2007N4X
230V	10	23-32	IDP2010N312	IDP2010N4	IDP2010N4X
230V	15	37-50	IDP2015N312	IDP2015N4	IDP2015N4X
230V	20	48-65	IDP2020N312	IDP2020N4	IDP2020N4X
230V	25	63-80	IDP2025N312	IDP2025N4	IDP2025N4X
230V	30	80-104	IDP2030N312	IDP2030N4	IDP2030N4X
230V	40	95-120	IDP2040N312	IDP2040N4	IDP2040N4X
230V	50	110-140	IDP2050N312	IDP2050N4	IDP2050N4X

### 460 Volt

Motor Voltage 60Hz	Max HP	Overload Relay Range	NEMA 12/3R	NEMA 4	NEMA 4X 304SS
460V	3	4.5-6.5	IDP4003N312	IDP403N4	IDP4003N4X
460V	5	6.0-8.5	IDP4005N312	IDP405N4	IDP4005N4X
460V	7.5	10-14	IDP4007N312	IDP407N4	IDP4007N4X
460V	10	13-19	IDP4010N312	IDP4010N4	IDP4010N4X
460V	15	18-25	IDP4015N312	IDP4010N4	IDP4010N4X
460V	20	24-32	IDP4020N312	IDP4020N4	IDP4020N4X
460V	25	29-42	IDP4025N312	IDP4025N4	IDP4025N4X
460V	30	36-52	IDP4030N312	IDP4030N4	IDP4030N4X
460V	40	45-63	IDP4040N312	IDP4040N4	IDP4040N4X
460V	50	60-80	IDP4050N312	IDP4050N4	IDP4050N4X
460V	60	65-90	IDP4060N312	IDP4060N4	IDP4060N4X
460V	75	80-110	IDP4075N312	IDP40754	IDP4075N4X
460V	100	110-150	IDP4100N312	IDP4100N4	IDP4100N4X

