

The NDP-Series Duplex Pump Control Panels consist of two NEMA rated Across-the-Line Magnetic motor starters in a common enclosure. The NDP comes with a fused disconnect and each starter has short circuit protection

Max HP	Motor Voltage	NEMA Starter Size	FLA Amps	NEMA 3R		NEMA 4		NEMA 4X	
7.5	200	1	27	013R		14		014X	
7.5	230	1	27	213R		214		214X	
10	380	1	27	313R		314		314X	
10	460	1	27	413R		414		414X	
10	575	1	27	513R		514		514X	
10	200	2	45	023R		24		024X	
15	230	2	45	223R		224		224X	
25	380	2	45	323R		324		324X	
25	460	2	45	423R		424		424X	
25	575	2	45	523R		524		524X	
25	200	3	90	033R		34		034X	
30	230	3	90	233R		234		234X	
50	380	3	90	333R		334		334X	
50	460	3	90	433R		434		434X	
50	575	3	90	533R		534		534X	
40	200	4	135	043R		44		044X	
50	230	4	135	243R		244		244X	
75	380	4	135	343R		344		344X	
100	460	4	135	443R		444		444X	
100	575	4	135	543R		544		544X	
75	200	5	270	053R	CF	54	CF	054X	CF
100	230	5	270	253R	CF	254	CF	254X	CF
150	380	5	270	353R	CF	354	CF	354X	CF
200	460	5	270	353R	CF	354	CF	354X	CF
200	575	5	270	353R	CF	354	CF	354X	CF

